

RIDGID®

K-4310 FXP™ Drum Machine



Powers Through the Toughest Jobs

FXP
TECHNOLOGY PLATFORM

The RIDGID® K-4310 FXP™ Drum Machine is RIDGID's most powerful drum machine, delivering best-in-class performance. Powered by the FXP Technology Platform, this machine lets you switch between the battery and power adapter for convenience and all-day runtime. The Cable Counter gives real-time feedback measuring cable distance in 3" to 10" lines on residential and commercial jobs, making this a valuable addition to your truck.

- **Performance:** RIDGID's most powerful drum machine features a Brushless DC Motor and spins up to 230 RPM
- **Power:** FXP Battery and Power Adapter provide continuous uptime and powerful performance
- **Real-Time Machine Feedback:** Cable Counter measures cable distance in drain line
- **Efficiency:** Quick-change drum allows for toolless setup and easy transport
- **Speed:** AUTOFEED® Technology advances and retrieves cable up to 28' (8.5 m) per minute with zero tools required for setup
- **Connected:** Create shareable job insights, maintenance reminders, and tool history with the RIDGID® Link app



SPECIFICATIONS

- Capacity 3" – 6" (5/8" Cable)
4" – 10" (3/4" Cable)
- Drum Capacity, 5/8" Drum 100' (30.5m) of 5/8" (16mm) Diameter Cable
- Drum Capacity, 3/4" Drum 125' (38.1m) of 5/8" (16mm) Diameter Cable,
100' (30.5m) of 11/16" (17.5mm) Diameter Cable
100' (30.5m) of 3/4" (20mm) Diameter Cable
- Maximum Reach 250' (76m)
- Power Source RIDGID® FXP Battery Pack or
FXP Power Adapter (*in development*)
- Motor Type Brushless DC Motor
- Watts 810 W
- Amps 15 A
- Voltage 54V DC Nominal
- No Load Output Speed 230 RPM
- Weight (No Cable) 123 lbs. (55.8 kg)
- Weight (w/100' of 5/8" Cable) ... 193 lbs. (87.5 kg)
- Weight (w/100' of 3/4" Cable) 237 lbs. (107.5 kg)
- Dimensions (Handle Down) 37" x 22" x 35" (940mm x 559mm x 889mm)
- Controls Main ON-OFF Switch, FOR/OFF/REV Switch, Pneumatic Foot Switch,
AUTOFEED® Cable Feed Unit Handle



*Drum includes 5/8" or 3/4" Pigtail. Cable sold separately.



ORDER INFORMATION

| CATALOG NO. | MODEL NO. | DESCRIPTION | WEIGHT (lb.) (kg) |
|-------------|------------|--|-------------------|
| 73048 | K-4310 FXP | K-4310 FXP 3/4" Drum Machine (3/4" Pigtail Only) with FXP Battery - 8.0 Ah (Qty-2) & Charger | 145.8 66.1 |
| 73073 | K-4310 FXP | K-4310 FXP 5/8" Drum Machine (5/8" Pigtail Only) with FXP Battery - 8.0 Ah (Qty-2) & Charger | 138.9 63.0 |

ACCESSORIES

| CATALOG NO. | MODEL NO. | DESCRIPTION |
|-------------|-----------|------------------------------|
| 70788 | RB-FXP40 | FXP Battery – 4.0 Ah |
| 70793 | RB-FXP80 | FXP Battery – 8.0 Ah |
| 70798 | RBC-FXP | FXP Battery Charger |
| 73093 | — | K-4310 FXP 3/4" Drum Only |
| 73098 | — | K-4310 FXP 5/8" Drum Only |
| 73083 | — | AUTOFEED® Assembly |
| 41697 | C-100 | 3/4" x 100' Inner Core Cable |
| 43647 | C-24 | 5/8" x 100' Inner Core Cable |

Note: Additional Drum Machine Cables & Tools Ordering Information can be found on RIDGID.com.



FXP Power Adapter
(In Development)

